

DISPERSION COMPENSATOR AND METHOD
OF COMPENSATING FOR DISPERSION

5

Background of the Invention:

Field of the Invention:

The invention lies in the field of optics technology. More specifically, the invention relates to an optical dispersion compensator, preferably for use preceding an optical transmission link or following an optical transmission link, comprising at least one optical input, at least one frequency demultiplexer (FDM) which splits incoming signals with an input spectrum into two frequency bands f_L and f_H and two transmission links (Mach-Zehnder-Arms) of different optical lengths each of which is supplied with a frequency band (f_L , f_H), the optically longer Mach-Zehnder arm being used as delay line, and then at least one frequency recombination unit in which the two spectrally divided signals are recombined and conducted to at least one optical output.

The invention also relates to a method of compensating for the dispersion of an optical signal, transmitted via an optical fiber, having a frequency spectrum composed of two frequency bands f_H and f_L . The frequency bands are split to one Mach-

Zehnder arm each, subjected to different propagation delays, and then combined again.

During the transmission of optical signals of a particular frequency spectrum (a particular band width) via an optical conductor of great length, for example an optical fiber, dispersion phenomena occur due to the frequency-dependent velocity of propagation of the light in the optical fibers, that is to say a distortion of the input light pulse/input bit sequence in dependence on the path length. This chromatic dispersion of the optical fibers limits the maximum distance which can be spanned with the high-bit-rate transmission systems. Thus, for example, the usual single-mode optical fibers with a dispersion of 17 ps/nm*km at a wavelength of 1550 nm allow a distance of only 80-100 km (50-65 miles) in 10 Gbit/s systems which can be spanned without dispersion compensation. Any further doubling of the transmission band width reduces the maximum distance which can be spanned roughly by a factor of 4. The dispersion of the optical fiber must then be correspondingly compensated for in the case of longer transmission links.

Due to their significance for the high-bit-rate transmission systems, there are a very large number of previously known methods for dispersion compensation. They can be roughly

divided into electronic compensation techniques and optical compensation techniques.

Among the electronic compensation methods, there are firstly
5 the pre-chirp techniques. They are based on generating a
negative frequency chirp of the laser diode, thus providing
for appropriate precompensation. Furthermore, a reduction of
the input band width can be achieved by suitable modulation
methods such as single-sideband modulation, duo-binary
10 modulation etc. and thus the maximum distance which can be
spanned can be increased, the bit rate remaining the same.

The electronic compensation techniques are generally quite
cumbersome and their implementation depends on the bit rate to
15 be transmitted. A further problem consists in that electronic
compensation techniques are not optically transparent.

In the optical compensation methods, attempts are made to
simulate the dispersion of the transmission link by a
20 corresponding opposite dispersion of the optical compensation
element as completely as possible. With an optimum simulation
of the dispersion including the higher-order dispersion terms
and disregarding the non-linear effects, a complete
compensation can be potentially achieved.

For the optical dispersion compensation, special dispersion compensating fibers (DCFs) were developed which are now widely used in optical transmission systems. In this case, a bit sequence passes through the appropriately dimensioned DCF either before or after the actual dispersive transmission link section. Given the dispersion values of the DCFs which are currently achieved, a DCF length of approximately 15 km is needed for compensating for a 100 km transmission link via standard single-mode fibers.

Although these DCFs are optically transparent and allow for multi-channel compensation, they suffer from not being very compact, have an attenuation which is not negligible, and have no adjustable dispersion. The length of the DCF must be appropriately readjusted for each transmission link which entails additional logistical problems.

Another optical compensation technique is based on the "chirped" Bragg gratings (implemented fiber-optically or integrated optically). Although the "chirped" Bragg gratings are somewhat more compact than the DCFs, they operate in reflection mode and must thus be combined with a circulator. Moreover, the dispersion band width of a grating is limited and each individual wavelength channel must be separately compensated for. Furthermore, Bragg gratings which can be adjusted over a wide range of dispersion cannot be easily

Sub A3
achieved because, in addition, the compensation band width and the reflection coefficient are dependent on the adjusted dispersion.

5 Another possibility consists in implementing dispersion compensation circuits by integrated optical means in planar technology, fiber-optically or volume-optically with the aid of interferometric configurations. The interferometric configurations are based on the use of asymmetric Mach-Zehnder
10 interferometers, ring resonators or the Fabry-Perot resonators.

Regarding the compensation techniques described above, relating to Mach-Zehnder, reference is had to the following
15 documents:

- Sub A4
- K. Takiguchi, K. Okamoto and K. Moriwaki, "Planar Lightwave Circuit Dispersion Equalizer", J. Lightwave Technol., vol. 14, pp. 2003-11, 1996;
 - K. Takiguchi, S. Kawanishi, H. Takara, A. Himeno. K. Hattori, "Dispersion Slope Equalizer for Dispersion Shifted
20 Fiber Using a Lattice-Form Programmable Optical Filter on a Planar Lightwave Circuit", J. Lightwave Technol., vol. 16, pp. 1647-56, 1998; and

- K. Jinguji, M. Kawachi, "Synthesis of Coherent Two-Port Lattice-Form Optical Delay-Line Circuit", J. Lightwave Technol., vol. 13, pp. 73-82, 1995;

5 Relating to ring resonators and Fabry-Perot, reference is had to the following reference:

- C.K. Madsen, G. Lenz, 'Optical All-Pass Filters for Phase Response Design with Applications for Dispersion Compensation', IEEE Photon. Technol. Lett., vol. 10, pp. 994-96, 1998.

The contents of the foregoing references are herewith incorporated by reference.

15 A technical problem of the above-mentioned interferometric structures consists in that, without cascading, they only provide for very limited dispersion compensation while simultaneously requiring a wide dispersion band width. The cascading necessary for this, in turn, unavoidably leads to a
20 structure which is increasingly more difficult to implement and is more complex.

Summary of the Invention:

25 The object of the present invention is to provide a dispersion compensator and a method for compensating for dispersion which

5 7
AB 5
overcome the above-noted deficiencies and disadvantages of the
prior art devices and methods of this general kind, and
wherein the system is capable of compensating for high
dispersion values without cascading a number of filter stages
and which, at the same time, has a wide band width.
Furthermore, the invention is intended to make it possible to
generate adjustable dispersion values.

10
With the above and other objects in view there is provided, in
accordance with the invention, an optical dispersion
compensator, comprising:

an optical input receiving an incoming signal having an input
spectrum;

15
a frequency demultiplexer connected to the input and
configured to split the incoming signal into two frequency
bands;

two transmission links formed as Mach-Zehnder arms connected
to the frequency demultiplexer and each receiving a respective
one of the two frequency bands, the transmission links
20 including an optically shorter transmission link and an
optically longer transmission link acting as a delay line;

a polarization converter connected in at least one of the two
transmission links; and

at least one frequency recombination unit connected to the two transmission links for recombining the signals received from the first and second transmission links, and an optical output for outputting the combined signal.

5

The dispersion compensator is preferably connected to receive the incoming signal from an optical transmission link and/or to output an optical signal recombined from the spectrally divided signals to an optical transmission link.

In further summary, the inventor proposes here a structure which provides for high dispersion compensation at any dispersion band width without cascading a number of filter stages. It is based on combining the two part-signals of an asymmetric Mach-Zehnder without forming interference in spite of an existing coherence. This is possible when the two signals are mutually orthogonally polarized when the signal is being recombined.

20 According to this concept of the invention, the optical dispersion compensator is improved - and specifically suitable for use preceding an optical transmission link or following an optical transmission link - in that there are provided at least one optical input, at least one frequency demultiplexer
25 (FDM) which splits incoming signals having an input spectrum into two frequency bands f_L and f_H and two transmission links

(Mach-Zehnder arms) of different optical lengths, each of which is supplied with a frequency band (f_L , f_H), the optically longer Mach-Zehnder arm being used as delay line, and then at least one frequency recombination unit in which the two

5 spectrally divided signals are recombined and conducted to at least one optical output, to such an extent that a polarization converter is provided in at least one Mach-Zehnder arm. This is preferably the Mach-Zehnder arm having the shorter optical length for constructional considerations.

According to the invention, this dispersion compensator can be mounted either preceding or following an optical data transmission link.

10
15 In accordance with an added feature of the invention, the frequency recombination unit is a TE/TM polarization combiner or a 3-dB coupler.

20 In accordance with an additional feature of the invention, at least one of the transmission links is split into two or more partial links. A driven $1 \times N$ switch and a driven $N \times 1$ switch are provided (N is an integer > 1) and N partial links are connected between the switches. Preferably, the $1 \times N$ switch and the $N \times 1$ switch are thermo- or electro-optically driven.

In accordance with another feature of the invention, a TE/TM phase shifter is connected in at least one of the transmission links. The TE/TM phase shifter may be connected behind, i.e., downstream of, the polarization converter.

5

With the above and other objects in view there is also provided, in accordance with the invention, an optical signal link which comprises a dispersion compensator as outlined above and a polarization controller connected upstream of the optical input of the dispersion compensator.

In accordance with a further preferred embodiment, the polarization controller is formed with two Mach-Zehnder arms and a phase shifter in at least one of the Mach-Zehnder arms.

Furthermore, the polarization controller further comprises a TE/TM divider at an input and a frequency recombination unit at an output thereof, and the two Mach-Zehnder arms of the polarization controller are connected between the TE/TM divider and the frequency recombination unit.

In accordance with again another feature of the invention, a polarization converter is connected in at least one of the Mach-Zehnder arms of the polarization controller.

25

The optical signal link is further characterized in that the polarization controller further comprises a bipolar polarization converter and mode sorter at an input thereof and a frequency recombination unit at an output thereof, and
5 wherein the at least two Mach-Zehnder arms of the polarization controller are connected between the bipolar polarization converter and mode sorter and the frequency recombination unit.

10 With the above and other objects in view there is also provided, in accordance with the invention, an optical signal link formed with the dispersion compensator outlined above and a polarization scrambler and a polarizer (TE mode or TM mode) connected to the optical input of the dispersion compensator.

15 As noted above, an advantageous refinement of the dispersion compensator provides for the multiplexer to be implemented in the form of a TE/TM polarization combiner. This is possible if the two recombination signals supplied orthogonally are
20 polarized in accordance with the respective principal axes (TE and TM). In this case, the two signals are theoretically combined without 3dB power loss. As an alternative, a 3dB coupler can also be used which then, however, causes the power loss.

In addition, the dispersion compensator can be designed in such a manner that at least one Mach-Zehnder arm, preferably the arm having the longer optical length and/or without polarization converter, is split into at least two part-links
 5 (into N part-links in general), in which case a drivable $1 \times N$ switch, a drivable $N \times 1$ switch and N part-links between the switches are provided. The result is that the delay time of the part-frequency band, and thus the achievable dispersion, becomes adjustable.

In this refinement of the dispersion compensator according to the invention, the $1 \times N$ switch and $N \times 1$ switch can be operated, for example, thermo-optically or electro-optically, without excluding other variants.

If there is no linearly polarized polarization state at the input of the compensator or there is a linearly polarized input state which does not correspond to the directions of the principal axis of the wave guides of the compensator and, at the same time, the wave guides of the compensator are anisotropically constructed, the two signals with the different frequency bands are no longer orthogonally polarized when they are being combined.

25 To recover the orthogonality in this case, it is also proposed in a special refinement of the invention that a fast

controllable TE/TM phase shifter is arranged in at least one transmission link of the Mach-Zehnder, preferably behind the polarization converter. This makes it possible to ensure the orthogonality of the recombination signals when they are being combined by suitably driving the TE/TM phase shifter in the case of anisotropic wave guides.

If the dispersion compensator is to be used following an optical signal link, it may be appropriate or even necessary to linearize the polarization state coming into the dispersion compensator. This can be done by using a polarization controller in front of the dispersion compensator. This polarization controller can be implemented by a TE/TM divider at the input and a frequency recombination unit (multiplexer) at the output, one of the two Mach-Zehnder arms being equipped with a polarization converter and one of the two Mach-Zehnders being equipped with a fast controllable phase shifter.

In another embodiment of the signal link, the polarization controller is implemented by means of a bipolar polarization converter and mode sorter at the input and a frequency recombination unit (multiplexer) at the output where here, too, one of the two Mach-Zehnder arms needs a fast controllable phase shifter.

When the dispersion compensation element is mounted after the transmission link, there is also the possibility of mounting a fast polarization scrambler in front of the compensator and then a TE mode or TM mode polarizer. This also provides for a homogenous linear input polarization state in the compensator, an additional 3dB power loss having to be accepted in this configuration.

With the above objects in view there is also provided, in accordance with the invention, a method of compensating for a dispersion of an optical signal. The method comprises the following method steps:

transmitting an optical signal via an optical fiber, the optical signal having a frequency spectrum composed of two frequency bands f_H and f_L , splitting the frequency bands into one Mach-Zehnder arm each, and subjecting the frequency bands to different propagation delays; and

recombining the two frequency bands transmitted in the two Mach-Zehnder arms and polarized orthogonally with respect to one another when they are combined.

In other words, in the method for compensating for dispersion of an optical signal transmitted via an optical fiber, having a frequency spectrum composed of two frequency bands f_H , f_L ,

the frequency bands being split to one Mach-Zehnder arm each, being subjected to different propagation delays and then being combined again, which is characterized in that the two frequency bands are polarized orthogonally with respect to one
5 another when they are combined.

It must also be pointed out that the compensator can be implemented fiber-optically, volume-optically and/or integrated optically. Naturally, care must be taken to see
10 that the components used do not generate any additional rotations in the polarization states.

Other features which are considered as characteristic for the invention are set forth in the appended claims.

Although the invention is illustrated and described herein as embodied in a dispersion compensator and method for
15 compensating for dispersion, it is nevertheless not intended to be limited to the details shown, since various
20 modifications and structural changes may be made therein without departing from the spirit of the invention and within the scope and range of equivalents of the claims.

The construction and method of operation of the invention,
25 however, together with additional objects and advantages thereof will be best understood from the following description

of specific embodiments when read in connection with the accompanying drawings.

Brief Description of the Drawings:

- 5 Fig. 1 is a diagrammatic view illustrating the elementary functions of an (integrated-optical, fiber-optical or volume-optical) dispersion compensator based on a frequency demultiplexer, an asymmetric Mach-Zehnder and a frequency recombination unit, according to the prior art;

Fig. 2 is a diagrammatic view illustrating the principle of dispersion compensation by cascading an asymmetric Mach-Zehnder interferometer;

15 Fig. 3 is a diagram illustrating dispersion compensation analogously to Fig. 1 but additionally with the installation of a polarization converter in one of the two interferometer arms;

- 20 Fig. 4 is a diagram showing dispersion compensation as in Fig. 3 but with adjustable delay line for the f_H band of the spectrum;

Fig. 5 is a diagram showing dispersion compensation as in Fig. 4 but expanded by a TE/TM phase shifter for compensating

Sub
A9 for birefringent wave guides ~~at any~~ homogenous elliptical
input polarization state;

Fig. 6a illustrates dispersion compensation as in Fig. 4 but
5 with a preceding polarization controller;

Fig. 6b illustrates another version of the dispersion
compensation as in Fig. 4 with a preceding polarization
controller; and

Fig. 7 illustrates dispersion compensation as in Fig. 4 but
expanded by a preceding polarization scrambler followed by a
TE polarizer.

15 Description of the Preferred Embodiments:

Referring now to the figures of the drawing in detail and
first, particularly, to Fig. 1 thereof, there is seen a
diagrammatic illustration of a prior art assembly for
compensating for dispersion with the aid of an asymmetric
Mach-Zehnder interferometer having an input 15 and two outputs
(output 1 and output 2) at 16. The elementary functions
necessary for compensating for dispersion such as the spectral
division of the signal with the aid of a frequency division
multiplexer (FDM) 1, the spectrum-dependent time delay ΔL ($\Delta \tau$)
25 and the signal recombination in a multiplexer 3 are

Sub
A11
implemented on a common starting ~~substrate~~ in the case of an integrated implementation.

In the example according to Fig. 1, the input frequency spectrum f_L , f_H of the signal is divided by the FDM 1 into two frequency bands f_H (high frequencies) and f_L (low frequencies) to the two Mach-Zehnder arms 4.1 and 4.2. As is also shown in Fig. 1, an adjustable phase shifter 2 for adjusting the phase difference $\Delta\phi$, which may be based on the thermo-optical or electro-optical effect, is additionally necessary for precise phase calibration in one of the interferometer arms. Following this, the separated signals are recombined via the multiplexer 3.

40
50
60
70
80
90
100
110
120
130
140
150
160
170
180
190
200
210
220
230
240
250
260
270
280
290
300
310
320
330
340
350
360
370
380
390
400
410
420
430
440
450
460
470
480
490
500
510
520
530
540
550
560
570
580
590
600
610
620
630
640
650
660
670
680
690
700
710
720
730
740
750
760
770
780
790
800
810
820
830
840
850
860
870
880
890
900
910
920
930
940
950
960
970
980
990
1000
1010
1020
1030
1040
1050
1060
1070
1080
1090
1100
1110
1120
1130
1140
1150
1160
1170
1180
1190
1200
1210
1220
1230
1240
1250
1260
1270
1280
1290
1300
1310
1320
1330
1340
1350
1360
1370
1380
1390
1400
1410
1420
1430
1440
1450
1460
1470
1480
1490
1500
1510
1520
1530
1540
1550
1560
1570
1580
1590
1600
1610
1620
1630
1640
1650
1660
1670
1680
1690
1700
1710
1720
1730
1740
1750
1760
1770
1780
1790
1800
1810
1820
1830
1840
1850
1860
1870
1880
1890
1900
1910
1920
1930
1940
1950
1960
1970
1980
1990
2000
2010
2020
2030
2040
2050
2060
2070
2080
2090
2100
2110
2120
2130
2140
2150
2160
2170
2180
2190
2200
2210
2220
2230
2240
2250
2260
2270
2280
2290
2300
2310
2320
2330
2340
2350
2360
2370
2380
2390
2400
2410
2420
2430
2440
2450
2460
2470
2480
2490
2500
2510
2520
2530
2540
2550
2560
2570
2580
2590
2600
2610
2620
2630
2640
2650
2660
2670
2680
2690
2700
2710
2720
2730
2740
2750
2760
2770
2780
2790
2800
2810
2820
2830
2840
2850
2860
2870
2880
2890
2900
2910
2920
2930
2940
2950
2960
2970
2980
2990
3000
3010
3020
3030
3040
3050
3060
3070
3080
3090
3100
3110
3120
3130
3140
3150
3160
3170
3180
3190
3200
3210
3220
3230
3240
3250
3260
3270
3280
3290
3300
3310
3320
3330
3340
3350
3360
3370
3380
3390
3400
3410
3420
3430
3440
3450
3460
3470
3480
3490
3500
3510
3520
3530
3540
3550
3560
3570
3580
3590
3600
3610
3620
3630
3640
3650
3660
3670
3680
3690
3700
3710
3720
3730
3740
3750
3760
3770
3780
3790
3800
3810
3820
3830
3840
3850
3860
3870
3880
3890
3900
3910
3920
3930
3940
3950
3960
3970
3980
3990
4000
4010
4020
4030
4040
4050
4060
4070
4080
4090
4100
4110
4120
4130
4140
4150
4160
4170
4180
4190
4200
4210
4220
4230
4240
4250
4260
4270
4280
4290
4300
4310
4320
4330
4340
4350
4360
4370
4380
4390
4400
4410
4420
4430
4440
4450
4460
4470
4480
4490
4500
4510
4520
4530
4540
4550
4560
4570
4580
4590
4600
4610
4620
4630
4640
4650
4660
4670
4680
4690
4700
4710
4720
4730
4740
4750
4760
4770
4780
4790
4800
4810
4820
4830
4840
4850
4860
4870
4880
4890
4900
4910
4920
4930
4940
4950
4960
4970
4980
4990
5000
5010
5020
5030
5040
5050
5060
5070
5080
5090
5100
5110
5120
5130
5140
5150
5160
5170
5180
5190
5200
5210
5220
5230
5240
5250
5260
5270
5280
5290
5300
5310
5320
5330
5340
5350
5360
5370
5380
5390
5400
5410
5420
5430
5440
5450
5460
5470
5480
5490
5500
5510
5520
5530
5540
5550
5560
5570
5580
5590
5600
5610
5620
5630
5640
5650
5660
5670
5680
5690
5700
5710
5720
5730
5740
5750
5760
5770
5780
5790
5800
5810
5820
5830
5840
5850
5860
5870
5880
5890
5900
5910
5920
5930
5940
5950
5960
5970
5980
5990
6000
6010
6020
6030
6040
6050
6060
6070
6080
6090
6100
6110
6120
6130
6140
6150
6160
6170
6180
6190
6200
6210
6220
6230
6240
6250
6260
6270
6280
6290
6300
6310
6320
6330
6340
6350
6360
6370
6380
6390
6400
6410
6420
6430
6440
6450
6460
6470
6480
6490
6500
6510
6520
6530
6540
6550
6560
6570
6580
6590
6600
6610
6620
6630
6640
6650
6660
6670
6680
6690
6700
6710
6720
6730
6740
6750
6760
6770
6780
6790
6800
6810
6820
6830
6840
6850
6860
6870
6880
6890
6900
6910
6920
6930
6940
6950
6960
6970
6980
6990
7000
7010
7020
7030
7040
7050
7060
7070
7080
7090
7100
7110
7120
7130
7140
7150
7160
7170
7180
7190
7200
7210
7220
7230
7240
7250
7260
7270
7280
7290
7300
7310
7320
7330
7340
7350
7360
7370
7380
7390
7400
7410
7420
7430
7440
7450
7460
7470
7480
7490
7500
7510
7520
7530
7540
7550
7560
7570
7580
7590
7600
7610
7620
7630
7640
7650
7660
7670
7680
7690
7700
7710
7720
7730
7740
7750
7760
7770
7780
7790
7800
7810
7820
7830
7840
7850
7860
7870
7880
7890
7900
7910
7920
7930
7940
7950
7960
7970
7980
7990
8000
8010
8020
8030
8040
8050
8060
8070
8080
8090
8100
8110
8120
8130
8140
8150
8160
8170
8180
8190
8200
8210
8220
8230
8240
8250
8260
8270
8280
8290
8300
8310
8320
8330
8340
8350
8360
8370
8380
8390
8400
8410
8420
8430
8440
8450
8460
8470
8480
8490
8500
8510
8520
8530
8540
8550
8560
8570
8580
8590
8600
8610
8620
8630
8640
8650
8660
8670
8680
8690
8700
8710
8720
8730
8740
8750
8760
8770
8780
8790
8800
8810
8820
8830
8840
8850
8860
8870
8880
8890
8900
8910
8920
8930
8940
8950
8960
8970
8980
8990
9000
9010
9020
9030
9040
9050
9060
9070
9080
9090
9100
9110
9120
9130
9140
9150
9160
9170
9180
9190
9200
9210
9220
9230
9240
9250
9260
9270
9280
9290
9300
9310
9320
9330
9340
9350
9360
9370
9380
9390
9400
9410
9420
9430
9440
9450
9460
9470
9480
9490
9500
9510
9520
9530
9540
9550
9560
9570
9580
9590
9600
9610
9620
9630
9640
9650
9660
9670
9680
9690
9700
9710
9720
9730
9740
9750
9760
9770
9780
9790
9800
9810
9820
9830
9840
9850
9860
9870
9880
9890
9900
9910
9920
9930
9940
9950
9960
9970
9980
9990
10000

This configuration represents a filter stage. The phase relationship of the waves interfering in the multiplexer 3 must not change too much as a function of the frequency in order to be able to achieve the desired compensation band widths without much intensity and time delay ripple. However, this requirement limits the maximum achievable delay time $\Delta\tau$, and thus the dispersion per filter stage.

Sub
A12
As a consequence, it is only possible to achieve large dispersion compensation over a ~~great~~ band width by cascading a number of asymmetric Mach-Zehnders (filter stages). Such an

Sub
A12

implementation, normally used in the prior art, is shown in Fig. 2. The individual asymmetric Mach-Zehnder interferometers are here connected to one another by directional couplers 5 and, at the same time, fulfill the functions of frequency division multiplex, frequency-dependent delay, and frequency division demultiplex.

Sub
A13

Due to the cascading, a progressive coherent overloading of the wave components of the two interferometer arms is generated. The greater the desired dispersion compensation with simultaneous large band width, the more cascading stages are required. Thus, the implementation becomes increasingly more difficult, especially since the optical path length or, respectively, the phase of each interferometer or, respectively, of each filter stage, must be precisely monitored. This may be done by a thermo-optical phase shifter. Configurations with virtually arbitrarily adjustable compensation values, possibly by means of adjustable couplers, are conceivable but again increase the complexity.

20

Fig. 3 shows a structure according to the invention of an optical dispersion compensator analogously to Fig. 1. Here, however, a polarization converter 6 is additionally inserted in the Mach-Zehnder arm 4 (interferometer arms). The aim is to achieve a signal recombination of two frequency bands without interference being formed due to their orthogonal

25

Sub
A14

polarization states. By appropriately dimensioning ΔL (difference in length of the Mach-Zehnder arms), time delays $\Delta \tau$ of the frequency band f_H can be achieved which have any magnitude, and this with a total band width of the signal $f_L + f_H$ which, at the same time, is of any magnitude.

Sub
A15

The assembly firstly consists of the frequency demultiplexer (FDM) 1 which divides the input spectrum into two frequency bands f_L and f_H . The FDM 1 ideally has a rectangular frequency response, i.e. having edges which drop off as steeply as possible. In the asymmetric Mach-Zehnder interferometer following, the two frequency bands f_L and f_H are subjected to a different propagation delay. In the case of isotropic and, at the same time, polarization-maintaining wave guides as is basically possible, for example, with an integrated optical form of implementation, the polarization input state as drawn in Fig. 3 can have any elliptical shape. The polarization states are specified by the configuration of the ellipses shown. The polarization converter then converts the signal of the Mach-Zehnder arm 4.1 from an arbitrarily elliptically polarized state into an elliptically polarized signal which is orthogonal thereto. This signal is then combined with the time-delayed signal from the Mach-Zehnder arm 4.2 in the multiplexer 3.

Sub A16
5 The multiplexer 3 in which the two frequency bands are combined and superimposed again may consist, in a simple implementation, of a broad band 3dB coupler which entails an additional power loss of about 3dB. In that case, an output of the multiplexer 3 can be used as monitor output. This can be used for monitoring the output power.

Sub A17
10 If, as shown in Fig. 3, the configuration consists of isotropic wave guides, an arbitrary elliptical polarization state of the input signal is permissible for its correct operation and the ellipse should be as identical as possible over the entire channel band width. In the case of a linear input polarization state with identical axes, the multiplexer can be implemented by a TE/TM polarization combiner which makes it possible to combine the signals without 3dB power loss.

Sub A18
20 In the case of weakly or non-dispersive wave guides, the dispersion of the transmission link is only roughly approximated by the two-stage time delay which, however, can lead to a considerable improvement in the signal. Suitable dimensioning of the delay line Δt can result in a two-stage time delay Δt of any magnitude without cascading which means considerable simplification, especially in the case of large
25 compensation values. Furthermore, the configuration manages

Sub
A18
without an adjustable phase shifter. The configuration thus needs no further corrective control with permanently set FDM, polarization converter and multiplexer.

Sub
A19
5 If the dispersion of the transmission link is to be simulated ideally, it can be attempted to use in the Mach-Zehnder arms dispersive wave guides which have to be especially developed for the purpose.

10 Fig. 4 shows a variant of the structure shown in Fig. 3 with adjustable time delay. For this purpose, two adjustable switches 7 and 8 which, depending on how they are driven, apply the f_H band of the spectrum to a corresponding delay line of different length 4.2.1 ... 4.2.N, are inserted in the Mach-
15 Zehnder arm 4.2. The switches can be driven, for example, thermo-optically or electro-optically. This configuration, too, does not need any phase shifter for precise phase calibration.

Sub
A20
20 The configuration shown in Fig. 4 requires, analogously to Fig. 3, ideally either an identical homogenous input polarization state over the entire channel frequency band width and, at the same time, isotropic wave guides, or a linear TE or TM input polarization state with arbitrarily
25 anisotropic wave guides to function correctly. The configurations according to Figs. 3 and 4 are, therefore,

Sub A20
 particularly suitable for dispersion compensation preceding the transmission link, for instance directly following the transmit laser with its defined linear polarization state.

5 If the configuration according to Fig. 4 can only be implemented by means of anisotropic wave guides, it is necessary to use an adjustable TE/TM phase shifter 9 in one of the two Mach-Zehnder arms to obtain correct operation of the dispersion compensator with an arbitrary homogenous elliptical
 10 input polarization state. As shown in Fig. 5, this phase shifter can be arranged, for example, following the polarization converter 6. The phase shifter 9 ensures that the two interferometer signals in the Mach-Zehnder arms 4.1 and 4.2 are orthogonal when they are combined. In this
 15 configuration, the TE/TEM phase shifter 9 must compensate for the accumulated difference in anisotropy of the two Mach-Zehnder arms.

For the general case of anisotropic wave guides of the
 20 dispersion compensator, the input polarization state can also be rotated by an additional preceding polarization controller in such a manner that it is linearly polarized and, at the same time, corresponds to one of the wave guide axes of the dispersion compensator.

Sub A22

Such an embodiment can be indicated especially if the dispersion compensator according to the invention is used following a transmission link. As a supplement to the embodiments known in the literature, Figs. 6a and 6b show two configurations which are possible for this purpose.

Sub
A23
FIG. 6a
The polarization controller 17 of the configurations according to Figs. 6a, 6b controls the polarization state in such a manner that it corresponds to the principal axes of the wave guides of the subsequent dispersion compensator 18 (TE or TM polarization). The principal axes of the wave guides of the subsequent dispersion compensator 18 are thus allowed to have any anisotropy. At the same time, the polarization controllers 17 of Figs. 6a, 6b can be used for compensating for the polarization mode dispersion to a limited extent.

Sub
A24
FIG. 6b
As a further variant for an application of the configurations following the transmission link as shown in Figs. 3 and 4, it would be conceivable to use a preceding fast polarization scrambler 13 followed by a TE or TM polarizer 14. In this case, the wave guides 4.1, 4.2 of the dispersion compensator 18 are allowed to have any anisotropy since the input polarization state of the light wave is oriented in the direction of one of the principal axes (TE or TM polarization) by the preceding polarizer 14. The polarization scrambler 13 is used either at the link input or directly before the

compensation element with the preceding polarizer. In any case, the polarizer should be used immediately preceding the actual compensator element.

- 5 As an example, Fig. 7 shows a configuration with a polarization scrambler 13 and TE polarizer 14 directly preceding the dispersion compensator 18.

In this configuration with polarization scrambler and downstream polarizer, an additional power loss of 3dB must be accepted.

All configurations described can be used for single-channel or multi-channel compensation in dependence on the nature of the transmission link. The configurations can be implemented either integrated-optically (on a common substrate in integrated or hybrid form), fiber-optically or with the aid of micro-optical (volume-optical) components.

- 20 Thus, the invention describes a method for compensating for dispersion and a dispersion compensator for carrying out the method, an optical signal being split into two frequency bands f_H and f_L and to two Mach-Zehnder arms, there being subjected to different propagation delays and the frequency bands subsequently being recombined and polarized orthogonally with respect to one another.
- 25

Overall, this invention provides a dispersion compensator and a method for compensating for dispersion which is able to compensate for high dispersion values without cascading a number of filter stages and, at the same time, has a great band width. Furthermore, the invention makes it possible also to generate adjustable dispersion values.